



AC-33

Super Portable, Versatile, Battery-Powered Stereo Acoustic Guitar Amp

Rich, deep, stereo sound to go — introducing the AC-33, the world's first battery-powered amp made specifically for acoustic guitar. Portable yet powerful, the AC-33 provides true stereo sound, Guitar and Mic/Line channels, custom-tailored effects, anti-feedback, and a Phrase Looper. But this amp was made to go places no amp has gone before. Thanks to its battery-power capability, the AC-33 lets you take your act anywhere: into the backwoods, onto the streets, or wherever your imagination leads you.



- → 30 watts (15 W + 15 W) of natural, stereo acoustic sound through twin speakers
- Runs on AC power or eight AA batteries (accepts rechargeable NiMH types)
- Dual-channel configuration: Guitar and Mic/Line channel
- Reverb, chorus and new ambience effects
- Advanced Anti-Feedback function

- ▶ Phrase Looper with 40 seconds of record time
- Stereo AUX input (connect MP3/CD players, etc.), headphone output
- ► Built-in tilt-back stand
- Removable battery cartridge for easy battery replacement





AC-33 Specification

■ Rated Power Output 30 W (15 W + 15 W) (when using the AC adaptor), 20 W (10 W + 10 W) (when using the Alkaline batteries) ■ Nominal Input Level (1 kHz) GUITAR CHANNEL: -10 dBu/1 M, MIC/ LINE CHANNEL: -50 dBu (LINE), AUX IN: -10 dBu ■ Nominal Output Level (1 kHz) LINE OUT: -10 dBu ■ Speakers 12 cm (5 inches) × 2 ■ Controls GUITAR CHANNEL: VOLUME Knob, Equalizer Knobs (BASS, MIDDLE, TREBLE), CHORUS Switch, MIC/LINE CHANNEL: VOLUME Knob, Equalizer Knobs (BASS, TREBLE), CHORUS Switch, AUX IN: LEVEL Knob, ANTI-FEEDBACK: ON/OFF Switch, LOOPER: REC/PLAY/OVERDUB Button, STOP/CLEAR Button, REVERB/AMBIENCE: REVERB/AMBIENCE Knob, Others: POWER Switch, MASTER Knob ■ Indicators LOOPER: REC, PLAY, OVERDUB, POWER: POWER ■ Connectors GUITAR CHANNEL: Input Jack (1/4" phone type), MIC/LINE CHANNEL: Input Connector (XLR type), Input Jack (TRS phone type), PHONES Jack (Stereo 1/4" phone type), AUX IN

Jacks (RCA phono type, Stereo miniature phone type), LINE OUT (L/MONO, R) Jacks (1/4" phone type), FOOT SW Jack: EFFECTS (TRS phone type), LOOPER (TRS phone type), DC IN Jack ■ Power Supply DC 13 V: AC Adaptor or Dry Battery (LR6 (AA) type) × 8 ■ Current Draw 490 mA ■ Expected battery life under continuous use Alkaline batteries: approximately 8 hours, Nickel-metal hydride batteries: approximately 9 hours (These figures will vary depending on the actual conditions of use.) ■ Dimensions 318 (W) × 223 (D) × 243 (H) mm/ 12-9/16 (W) × 8-13/16 (D) × 9-5/8 (H) inches ■ Weight 4.7 kg/10 lbs 6 oz (Excluding Batteries) ■ Accessory Owner's Manual, AC Adaptor, AC Cord ■ Options Foot Switch: BOSS FS-5U, FS-6, Connection Cable: Roland PCS-31L, PCS-33

* 0 dBu = 0.775 Vrms

* The specifications are subject to change without notice.