

# BK-9

## Backing Keyboard

SuperNATURAL

Virtual Tone Wheel

MIDI  
VISUAL  
CONTROL

V-LINK

D-BEAM

GENERAL  
MIDI2

XG

XG  
XGlite

mp3

USB

USB  
MEMORY

Roland  
Wireless  
Connect

SMF  
LYRICS

## A World of Music at Your Command

The BK-9 Backing Keyboard is the new flagship instrument in the acclaimed BK series, bringing together sensational sounds, top-class rhythms, and an incredible selection of premium features. You have a world of music under fingertip control, with a massive sound selection—including Roland's renowned SuperNATURAL sounds—and a huge range of completely remastered rhythm accompaniments in nearly every musical genre, from classic to modern.

An innovative dual LCD system and intuitive panel layout make it easy to direct your virtual band, while powerful effects and assignable real-time controls let you select and shape sounds with ease.

With numerous additional highlights such as USB song playback/recording, an onboard 16-track sequencer, Rhythm Composer, and much more, the BK-9 is a powerhouse music machine for professional performing, song composition, and casual enjoyment at home.



- Flagship 76-note instrument with top-level sounds, industry-leading auto-accompaniment features, and a lightweight, mobile design
- Over 1,700 sounds and 70 drum kits, including 22 SuperNATURAL sounds and 500 all-new tones
- Legendary Virtual Tone Wheel organs, with dedicated harmonic bars for authentic vintage organ performance
- 540 rhythms (including 25 new rhythms), remastered for exceptional audio quality; over 1000 Music Assistants onboard
- Five independent multi-effects engines (MFX), plus dedicated mastering effects
- All-new user interface with intuitive panel layout, powerful dual LCD system, and Mixer function
- Professional 16-track sequencer and built-in Rhythm Composer; Chord Loop and Audio Key functions
- Song playback/recording, unlimited Performance List storage, and more from convenient USB memory
- XLR mic input with dedicated reverb effect; composite video output for displaying lyrics and photos
- Compatible with Apple iOS devices via Roland Wireless Connect; supports USB connection to iPad with Apple's iPad Camera Connection Kit
- Free iOS apps include BK Partner, Lyrics Viewer, Air Recorder, and more



# BK-9

## Backing Keyboard

### Multi-Effects and Onboard Mixing

Five independent multi-effects engines (MFX) offer an enormous range of sound processing possibilities, with three MFX dedicated to rhythms and two MFX dedicated to real-time parts. Global reverb and chorus effects are available as well, along with two mastering processors that allow you to optimize the sound of the rhythm and real-time sections separately to suit performance venues and add final polish for recordings. A great new feature for live playing is the Mixer function, which gives you instant adjustment of rhythm and real-time part levels, MFX parameters, and more using the harmonic bars on the front panel.

### Powerful Tools for Creativity

A built-in 16-track sequencer provides a professional platform for composing and editing SMF data, while the Rhythm Composer lets you create and customize your own rhythms with ease. The convenient Chord Loop feature allows you to record and save chord sequences to drive the rhythms, great for generating on-the-fly backing patterns for two-handed solo/melody playing or preparing complete song arrangements for live performance, practice, or composition in the sequencer. With the Audio Key function, audio files stored on USB memory can be assigned to the top seven keyboard keys for quick-access playback while performing. Additionally, BK-9 performances can be easily recorded directly to USB memory as CD-ready WAV audio.

### Extras for Entertaining

If you sing or work with a vocalist, you'll appreciate the BK-9's convenient XLR microphone input, which features phantom power, a dedicated reverb effect, and easily accessible front-panel controls. A composite Video Out jack is also provided, allowing you to display embedded MP3/SMF lyrics and chord symbols on an external video monitor for performance assistance or sing-along entertaining. Photo slideshows can be displayed as well, letting your audience enjoy custom images while listening to your music.

#### Gallery





# BK-9

## Backing Keyboard

### Roland Wireless Connect and Free iOS Apps

The BK-9 is compatible with Roland Wireless Connect, which provides cable-free communication with Apple's iPhone, iPad, or iPod touch via Roland's optional WNA1100-RL Wireless USB Adapter. An iPad can also be connected directly to the BK-9 with a USB cable using Apple's iPad Camera Connection Kit. Many free iOS apps are available to enhance your BK-9 experience, including Air Recorder for jamming and capturing performances (iPhone/iPad), BK Partner for selecting tones and rhythms (iPad), Lyrics Viewer for displaying SMF lyrics (iPad), and a number of others.



### BK-9 Specifications

---

#### [Display Type]

2 displays 160 x 160 pixels, graphic LCD (backlit)

#### [Keyboard]

##### - Keyboard Type

76 velocity sensitive keys

##### - Key Touch

High, Medium, Low, Fixed

##### - Keyboard Modes

Organ, Piano

#### [Sound Generator]

##### - Max. Polyphony

128 voices (GM2/GS/XGlite compatible)

##### - Tones

1718 (Included 22 SuperNATURAL) + User Tone.

##### - Favorite Tone

Possibility to create four lists (UPPER1, UPPER2, LOWER, M. BASS) of 10 frequently used sounds and recall them instantly

##### - Drum Sets

77

##### - Multitimbral Parts

4 keyboard parts (UPPER1, UPPER2, LOWER, M. BASS) + MELODY INTELLIGENT + 16 song parts

##### - Master Tuning

415.3 to 466.2 Hz

##### - Key Control (Transpose)

-6 to +5 in semitones (for rhythm, SMF, mp3/WAVE)

#### [Organ Section]

##### - Harmonic Bar

16', 5-1/3', 8', 4', 2-2/3', 2', 1-3/5', 1-1/3', 1' + LEVEL

##### - Vibrato/Chorus

V-1/V-2/V-3/C-1/C-2/C-3

##### - Percussion

2nd/3rd, Soft, Slow

##### - Rotary Sound

Slow/Fast, Brake, Level

##### - Tone Wheel Type

50/60/70

##### - Amplifier Type

TYPE 1/TYPE 2/TYPE 3/TYPE 4/ TYPE 5

#### [Effects]

##### - Real Time Parts (UPPER1, UPPER2, LOWER, M. BASS)

Reverb and Chorus: selectable via Tone Part effects

2 Mfx (84 Mfx Editable Macro) (selectable via Tone Part effects)

Part EQ

##### - Rhythms/SMF section

Reverb: 8 types (selectable via Makeup Tools)

Chorus: 8 types (selectable via Makeup Tools)

3 Mfx (84 Mfx Editable Macro) (selectable via Makeup Tools)

Part EQ

##### - MIC

2-band EQ + gain for each band , Reverb

#### [Backing Section]

##### - Rhythms

Over 500 in 10 "Rhythm" families

##### - Real-time Player

Rhythms (STL), SMF (Format 0/1), KAR, mp3, WAVE

##### - Tempo Change

20 to 250 BPM for SMF and rhythms

##### - Time Stretch

75 to 125% for mp3 and WAVE

##### - One Touch Memories

4 suitable tones for each rhythm (Programmable)

##### - Track Mute

For Rhythms/SMF

##### - Center Cancel

For mp3/WAVE

##### - Rhythm Composer

Internal Rhythm Composer

##### - Rhythm and SMF Makeup Tools

Instrument-oriented editing

#### [Audio Recording]

##### - Media

USB Flash memory

##### - Save Format

Audio files (WAVE 44.1 kHz, 16-bit linear)

MIDI files (SMF)

#### [Sequencer]

##### - 16 Track Sequencer

Internal 16 tracks MIDI sequencer with microscope and macro editing functions

### BK-9 Specifications

---

#### - Chord Loop

Loop/Sequencer Mode

#### [Metronome]

##### - Time Signature

1 to 32/16, 1 to 32/8, 1 to 32/4, 1 to 32/2

##### - Mode

Always, Play, Rec

##### - Count In

Off, 1 bar, 2 bars

##### - Volume

Internal and external by METRONOME OUT jack

#### [Performance Memories]

##### - Performance Lists

Unlimited number (storage on USB memory)

Over 1000 "Music Assistant" memories (internal memory)

5 "Factory Song" memories (internal memory)

##### - Performance Memories per List

Max. 999

#### [Search Function]

Quick location of Rhythms, and Songs on the connected USB memory

#### [Demo]

Yes

#### [Lyrics]

SMF, mp3/WAVE, mp3+CDG (mp3+CDG on video output socket only)

#### [Slideshow]

Picture folder linked to songs (recommended resolution: 512 x 384 or 1024 x 768 pixels)

#### [Panel Controls]

##### - Rotary Encoder

Data dial with push switching function

##### - VOLUME

1 knob

##### - AUDIO IN

1 knob

##### - MIC VOLUME

1 knob

##### - MIC REVERB

1 knob

##### - BALANCE (Backing/Keyboard)

1 knob

##### - Pitch Bend/Modulation Lever

1

##### - Mixer/Harmonic Bars Section

10 sliders

##### - D-BEAM Controller

1

##### - Assign Switches

4

#### [Connectors]

##### - Audio OUTPUT Jacks (R, L/Mono)

1/4" phone type

##### - PHONES Jack

Stereo 1/4" phone type

##### - Audio INPUT Jack (R, L/Mono)

1/4" phone type

##### - MIC IN

1/4 inch phone type/XLR type (Phantom power switch OFF/ON)

##### - METRONOME OUT

1/4" phone type

##### - MIDI Connectors

THRU, IN, OUT (Visual Control function)

##### - USB Ports

USB COMPUTER connector (Type B, reception and transmission of MIDI data)

USB MEMORY (Type A, data storage devices)

##### - Foot pedal Jacks

HOLD, EXPRESSION, CONTROL (assignable)

##### - FC-7 PEDAL

1 socket (assignable)

##### - VIDEO OUTPUT Jack

RCA-type (CVBS, PAL or NTSC - selectable)

#### [General Specifications]

##### - Power Supply

AC adaptor (PSB-1U adaptor)

##### - Current Draw

1100 mA

##### - Auto Off Function

Off, 10min, 30min, 240min

# BK-9

## Backing Keyboard

### BK-9 Specifications

---

#### - Dimensions

Without music rest:

1251 (W) x 345 (D) x 123 (H) mm

49-1/4 (W) x 13-5/8 (D) x 4-7/8 (H) inches

Including music rest:

1251 (W) x 445 (D) x 308 (H) mm

49-1/4 (W) x 17-9/16 (D) x 12-1/8 (H) inches

#### - Weight

9.4 kg (excluding AC adaptor and music rest)

20 lbs 12 oz (excluding AC adaptor and music rest)

#### [Accessories]

Owner's Manual

PSB-1U AC Adaptor

Power Cord (for connecting the AC adaptor)

Music Rest

#### [Options (sold separately)]

##### - USB

USB Flash Memory (M-UF-series)

Wireless USB Adaptor (WNA1100-RL)

#### - Pedals

DP-series/BOSS FS-5U Pedal Switch

Expression EV-5, EV-7

FC-7 Footswitch

#### - Microphone

Roland DR Series

#### - Headphone

Roland RH Series

#### - Vocal Performer

VE-5

VE-20

#### - Amplifier

CM-110

CM-220

#### - Stand

KS-12

All specifications and appearances are subject to change.

\*Apple, the Apple logo, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries. App Store is a service mark of Apple Inc.

