



(CUBE-20XL/40XL/80XL)

New CUBEs with Heavy Attitude

With over one million CUBE amps sold and going strong, Roland continues to push the envelope with innovative amp technology and design. Today, the top-selling CUBE amp family gets another shot of adrenaline with the new CUBE-XL series, comprising four screamin' amps: the 15XL, 20XL, 40XL, and 80XL. The CUBE-XL amps turn up the heat with new, ultra-heavy COSM amp models, hard-rockin' effects, onboard phrase looping, and more. From crystal clean to crushing metal, the XL line provides a mouth-watering menu of COSM amps and effects, including the massive Extreme, Heavy Octave, and Metal Zone, plus the legendary JC-120, Acoustic Guitar Simulator, vintage Spring Reverb, and more (see below for the specific features of each amp).

All amps in the XL series offer switchable Lead and Clean channels, with the 20XL, 40XL and 80XL providing a third Solo channel.

Hard, heavy, and tough as nails . . . the new CUBE XL series will breathe fire into your music!



■ CUBE-XL Series Comparison Chart

| | CUBE-80XL | CUBE-40XL | CUBE-20XL | CUBE-15XL |
|--------------------|--------------------------|-------------------------|-------------------------|----------------------|
| Rated Power Output | 80W | 40W | 20W | 15W |
| Speaker | 30cm (12 inches) | 25cm (10 inches) | 20cm (8 inches) | 20cm (8 inches) |
| Amp Channel | JC CLEAN/LEAD (10 types) | JC CLEAN/LEAD (9 types) | JC CLEAN/LEAD (6 types) | CLEAN/LEAD (4 types) |
| EFX | 5 types | 5 types | 6 types | — |
| Delay | ○ | ○ | ○ | — |
| Reverb | SPRING, PLATE | SPRING, PLATE | SPRING, REVERB(PLATE) | — |
| SOLO Function | ○ (Memory) | ○ (Memory) | ○ (Boost) | — |
| Looper | ○ (80sec.) | ○ (80sec.) | — | — |
| Power Squeezer | — | ○ | ○ | ○ |
| Tuner | ○ | ○ | ○ | — |
| AUX IN | ○ | ○ | ○ | ○ |

CUBE-80XL

COSM



- ▶ 80-watt guitar amp with 12" high-performance speaker
- ▶ Three footswitchable channels, including JC Clean, Lead, and Solo with memory capability
- ▶ 11 COSM amp models, including the new Extreme amp
- ▶ Eight effects, including the new Heavy Octave and COSM vintage Spring Reverb
- ▶ 80-second Phrase Looper built in
- ▶ Three-band EQ plus Presence control for fine-tuning your sound
- ▶ Hands-free channel switching via footswitch (sold separately)

CUBE-80XL Specifications

■ **Rated Power Output** 80 W ■ **Nominal Input Level** INPUT: -10 dBu/1 M Ω , AUX IN: -10 dBu
 ■ **Speaker** 30 cm (12 inches) ■ **Controls** POWER Switch, CH SELECT Switch, TUNER Switch [JC CLEAN Channel] BRIGHT Switch, VOLUME Knob [LEAD Channel] TYPE Switch [ACOUSTIC SIM, BLACK PANEL, DLX COMBO, BRIT COMBO, TWEED, CLASSIC STACK, METAL STACK, R-FIER STACK, EXTREME, DYNA AMP] GAIN Knob, VOLUME Knob [SOLO] ON/OFF, MEMORY Switch, VOLUME Knob [EQUALIZER] BASS Knob, MIDDLE Knob, TREBLE Knob [PRESENCE] PRESENCE Knob [EFX] EFX Knob [CHORUS, FLANGER, PHASER, TREMOLO, HEAVY OCTAVE] [DELAY/LOOPER] REC/PLAY/DUB Switch, TAP/STOP Switch, DELAY/LOOPER Knob [DELAY, LOOPER] [REVERB] REVERB Knob [SPRING, PLATE] [FOOT SW] FOOT SW TYPE Switch (FS-5L, FS-5U)
 ■ **Indicators** JC CLEAN Channel, LEAD Channel, TUNER, SOLO, EFX, DELAY/LOOPER, REC/PLAY/

DUB, REVERB ■ **Connectors** INPUT Jack (1/4-inch phone type), AUX IN Jack (Stereo miniature phone type), LINE OUT Jack (1/4-inch phone type), RECORDING OUT/PHONES Jack (Stereo 1/4-inch phone type), EXT SPEAKER Jack (1/4-inch phone type)*, FOOT SW Jack (TIP: CH SELECT, RING:SOLO) (1/4-inch TRS phone type), FOOT SW Jack (TIP:EFX, RING:REVERB) (1/4-inch TRS phone type), FOOT SW Jack (TIP:DELAY/REC/PLAY/DUB, RING:TAP/STOP) (1/4-inch TRS phone type) *When connecting to an external speaker, make sure the speaker conforms to the following specifications. Impedance: 8 Ω or less, Allowable power input: 80 watts or greater ■ **Power Consumption** 75 W ■ **Dimensions** 440 (W) x 265 (D) x 440 (H) mm / 17-3/8 (W) x 10-7/16 (D) x 17-3/8 (H) inches ■ **Weight** 16 kg / 35 lbs 5 oz ■ **Accessory** Owner's Manual ■ **Options** Foot Switch (BOSS FS-5L, FS-5U, FS-6)

CUBE-40XL

COSM



- ▶ 40-watt guitar amp with 10" high-performance speaker
- ▶ Three footswitchable channels, including JC Clean, Lead, and Solo with memory capability
- ▶ 10 COSM amp models, including the new Extreme amp
- ▶ Eight effects, including the new Heavy Octave and COSM vintage Spring Reverb
- ▶ 80-second Phrase Looper built in
- ▶ Power Squeezer for full gain at low volume
- ▶ Hands-free channel switching via footswitch (sold separately)

CUBE-40XL Specifications

■ **Rated Power Output** 40 W ■ **Nominal Input Level** INPUT: -10 dBu/1 M Ω , AUX IN: -10 dBu
 ■ **Speaker** 25 cm (10 inches) ■ **Controls** POWER Switch, CH SELECT Switch, TUNER Switch, POWER SQUEEZER Switch, [JC CLEAN Channel] VOLUME Knob [LEAD Channel] TYPE Switch [ACOUSTIC SIM, BLACK PANEL, BRIT COMBO, TWEED, CLASSIC STACK, METAL STACK, R-FIER STACK, EXTREME, DYNA AMP], GAIN Knob, VOLUME Knob [SOLO] ON/OFF, MEMORY Switch, VOLUME Knob [EQUALIZER] BASS Knob, MIDDLE Knob, TREBLE Knob [EFX] EFX Knob [CHORUS, FLANGER, PHASER, TREMOLO, HEAVY OCTAVE] [DELAY/LOOPER] REC/PLAY/DUB Switch, TAP/STOP Switch, DELAY/LOOPER Knob [DELAY, LOOPER] [REVERB] REVERB Knob [SPRING, PLATE] ■ **Indicators** JC CLEAN Channel, LEAD Channel, TUNER, SOLO, EFX, DELAY/

LOOPER, REC/PLAY/DUB, REVERB, POWER SQUEEZER ■ **Connectors** INPUT Jack (1/4-inch phone type), AUX IN Jack (Stereo miniature phone type), RECORDING OUT/PHONES Jack (Stereo 1/4-inch phone type), FOOT SW Jack (TIP: CH SELECT, RING:SOLO) (1/4-inch TRS phone type), FOOT SW Jack (TIP:EFX, RING: REVERB) (1/4-inch TRS phone type), FOOT SW Jack (TIP:DELAY/REC/PLAY/DUB, RING: TAP/STOP) (1/4-inch TRS phone type) ■ **Power Consumption** 43 W ■ **Dimensions** 385 (W) x 265 (D) x 385 (H) mm / 15-3/16 (W) x 10-7/16 (D) x 15-3/16 (H) inches ■ **Weight** 10 kg / 22 lbs 1 oz
 ■ **Accessory** Owner's Manual ■ **Options** Foot Switch (BOSS FS-5L, FS-5U, FS-6)

CUBE-20XL

COSM



- ▶ 20-watt guitar amp with 8" high-performance speaker
- ▶ Two channels: Independent JC Clean and Lead plus Solo function for extra boost
- ▶ Six Lead types, including the new Extreme amp
- ▶ Nine effects, including the new Heavy Octave and COSM vintage Spring Reverb
- ▶ Power Squeezer for full gain at low volume
- ▶ Convenient audible tuner lets you tune your guitar without unplugging

CUBE-20XL Specifications

■ **Rated Power Output** 20 W ■ **Nominal Input Level** INPUT: -10 dBu/1 M Ω , AUX IN: -10 dBu
 ■ **Speaker** 20 cm (8 inches) ■ **Controls** POWER Switch, CH SELECT Switch, TUNER Switch, POWER SQUEEZER Switch, [JC CLEAN Channel] VOLUME Knob [LEAD Channel] TYPE Switch [ACOUSTIC SIM, OVERDRIVE, DISTORTION, METAL, METAL STACK, EXTREME], GAIN Knob, VOLUME Knob [EQUALIZER] BASS Knob, MIDDLE Knob, TREBLE Knob [EFX/SOLO] EFX/SOLO Knob [CHORUS, FLANGER, PHASER, TREMOLO, SOLO, HEAVY OCTAVE] [DELAY/REVERB] DELAY/REVERB Knob [DELAY, REVERB, SPRING] ■ **Indicators** JC CLEAN Channel, LEAD Channel,

TUNER, EFX/SOLO, POWER SQUEEZER ■ **Connectors** INPUT Jack (1/4-inch phone type), AUX IN Jack (Stereo miniature phone type), FOOT SW Jack (TIP: CH SELECT, RING: EFX/SOLO) (1/4-inch TRS phone type) RECORDING OUT/PHONES Jack (Stereo 1/4-inch phone type) ■ **Power Consumption** 24 W ■ **Dimensions** 385 (W) x 240 (D) x 385 (H) mm / 15-3/16 (W) x 9-1/2 (D) x 15-3/16 (H) inches ■ **Weight** 9 kg / 19 lbs 14 oz ■ **Accessory** Owner's Manual ■ **Options** Foot Switch (BOSS FS-5U, FS-6)

CUBE-15XL



- ▶ 15-watt guitar amp with 8" high-performance speaker
- ▶ Two channels: independent Clean and Lead
- ▶ 3 authentic BOSS Lead tones, including METAL ZONE plus new EXTREME
- ▶ Power Squeezer for full gain at low volume
- ▶ AUX IN jack to connect portable music players

CUBE-15XL Specifications

■ **Rated Power Output** 15 W ■ **Nominal Input Level** INPUT: -10 dBu/1 M Ω , AUX IN: -10 dBu
 ■ **Speaker** 20 cm (8 inches) ■ **Controls** POWER Switch, SELECT Switch, POWER SQUEEZER Switch, [CLEAN Channel] VOLUME Knob [LEAD Channel] TYPE Switch [OVERDRIVE, DISTORTION, METAL ZONE, EXTREME], GAIN Knob, VOLUME Knob, [EQUALIZER] BASS Knob, MIDDLE Knob,

TREBLE Knob ■ **Indicators** CLEAN Channel, LEAD Channel ■ **Connectors** INPUT Jack (1/4-inch phone type), AUX IN Jack (Stereo miniature phone type), RECORDING OUT/PHONES Jack (Stereo 1/4-inch phone type) ■ **Power Consumption** 18 W ■ **Dimensions** 335 (W) x 240 (D) x 335 (H) mm / 13-3/16 (W) x 9-1/2 (D) x 13-3/16 (H) inches ■ **Weight** 7.2 kg / 15 lbs 14 oz ■ **Accessory** Owner's Manual