



# World's First AA Battery-Powered Stereo Keyboard Amp!

With the new KC-110 stereo keyboard amplifier, Roland adds another great amp to its lineup, as well as another "World's First" title to its pedigree. The KC-110 is the first fully stereo, pro-quality keyboard amp that can be powered by eight AA batteries. Take this amp anywhere, plug in, and experience the rich, spatial sound that has become a Roland trademark.



- ▶ World's first AA battery-powered stereo keyboard amp!
- ▶ Runs on eight AA batteries, eight AA rechargeable batteries, or AC power (adaptor included)
- ▶ Highly efficient 30 watts ( 15 W + 15 W ) stereo amplifier with two 6.5" ( 16 cm ) speakers and two tweeters
- ▶ High-quality stereo digital effects built in: reverb, chorus, "Wide" chorus, and EQ; effects on/off can be controlled with optional footswitch
- ▶ Three independent channels with volume control
- ▶ XLR Mic/1/4" instrument input, two stereo inputs, stereo AUX input, stereo line outputs and headphone output
- ▶ Mounts on a speaker stand (optional speaker stand available)
- ▶ Built-in tilt-back stand, or place on ST-A95 Stand (optional)
- ▶ Removable battery cartridge for easy battery replacement



■ KC-110 on optional Speaker Stand (ST-A95)



### KC-110 Specifications

■ **Rated Power Output** 30 W (15 W + 15 W) (when using the AC adaptor), 20 W (10 W + 10 W) (when using the Alkaline batteries) ■ **Nominal Input Level (1 kHz)** Input CH 1 (MIC/LINE): -50 to -20 dBu, CH 2, 3 (LINE): -20 dBu, AUX IN: -10 dBu ■ **Nominal Output Level** LINE OUT: -10 dBu ■ **Speakers** 16 cm (6.5 inches) x 2, Tweeter x 2 ■ **Controls** CH 1 (MIC/LINE) Level Knob, CH 2 (LINE) Level Knob, CH 3 (LINE) Level Knob, EFFECT Knob, EQUALIZER: LOW Knob, HIGH Knob, VOLUME Knob, AUX IN LEVEL Knob, POWER Switch ■ **Indicator** POWER ■ **Connectors** CH 1 Input Connector (XLR type), CH 1 Input Jack (1/4" phone type), CH 2 Input (L/MONO, R) Jacks (1/4" phone type), CH 3 Input (L/MONO, R) Jacks (1/4" phone type), AUX IN Jacks (RCA phono type, Stereo miniature phone type), LINE OUT (L/MONO, R)

Jacks (1/4" phone type), PHONES Jack (Stereo 1/4" phone type), FOOT SW Jack (TRS phone type), DC IN Jack ■ **Power Supply** DC 13 V: AC Adaptor or Dry Battery (LR6 (AA) type) x 8 ■ **Current Draw** 550 mA ■ **Expected battery life under continuous use** Alkaline batteries: approximately 7 hours, Nickel-metal hydride batteries: approximately 8 hours (These figures will vary depending on the actual conditions of use.) ■ **Dimensions** 420 (W) x 244 (D) x 320 (H) mm/16-9/16 (W) x 9-5/8 (D) x 12-5/8 (H) inches (excluding batteries) ■ **Weight** 7.3 kg/16 lbs 2 oz (Excluding Batteries) ■ **Accessory** Owner's Manual, AC Adaptor, AC Cord ■ **Options** Speaker Stand: ST-A95, Foot Switch: BOSS FS-5U (EFFECT)

\* 0 dBu = 0.775 Vrms

\* The specifications are subject to change without notice.